

SAMPLING OF SIGNALS AND IMAGES.

1. Show that if  $f(x) = \frac{1}{T}\chi_{[-\frac{T}{2}, \frac{T}{2}]}(x)$ ,  $x \in \mathbb{R}$ , then

$$\mathcal{F}(f)(\xi) = \frac{\sin T\pi\xi}{T\pi\xi}, \quad \xi \in \mathbb{R}.$$

(The function  $h(t) = \frac{\sin \pi\xi}{\pi\xi}$  is called the *sinc* (*sinus cardinalis*) function and plays an important rôle in signal processing.)

2. Let  $f(x) = e^{-4\pi^2x^2}$ ,  $x \in \mathbb{R}$ . Show that

$$\mathcal{F}(f)(\xi) = \frac{1}{2\sqrt{\pi}}e^{-\xi^2/4}, \quad \xi \in \mathbb{R}.$$

3. Show that the *Gaussian chirp* given by  $f(x) = e^{-(a-ib)4\pi^2x^2}$ ,  $x \in \mathbb{R}$ , satisfies

$$\mathcal{F}(f)(\xi) = \frac{1}{2\sqrt{\pi}} \frac{1}{\sqrt{a-ib}} e^{-\frac{(a+ib)\xi^2}{4(a^2+b^2)}}, \quad \xi \in \mathbb{R}.$$

4. Show that if  $\varphi \in \mathcal{M}$ , the mapping  $U$  given by  $U(\varphi)(x, \xi) = e^{-2\pi i x \xi} \varphi(x, \xi)$ , belongs to  $\widetilde{\mathcal{M}}$ . Moreover, show that  $U^*(\widetilde{\varphi})(x, \xi) = e^{2\pi i x \xi} \widetilde{\varphi}(x, \xi)$ , where  $U^*$  denotes the adjoint to  $U$ . (The spaces  $\mathcal{M}$  and  $\widetilde{\mathcal{M}}$  have been defined in class.)

5. Let  $V_T$  be the space of functions in  $L^2(\mathbb{R})$  such that  $\text{supp } \mathcal{F}(f) \subset [-\frac{T}{2}, \frac{T}{2}]$ . Show that if  $h_T(x) = \frac{\sin(\pi T x)}{\pi T x}$ , then  $\left\{ h_T(x - \frac{k}{T}) \right\}_{k=-\infty}^{k=\infty}$  is an orthogonal basis of  $V_T$ . If  $f \in V_T$  prove that

$$f\left(\frac{k}{T}\right) = T \int_{-\infty}^{\infty} f(x) h_T\left(x - \frac{k}{T}\right) dx = \langle f, h_T(\cdot - \frac{k}{T}) \rangle.$$

6. Let  $f \in L^1(\mathbb{R})$  and  $\text{supp } \mathcal{F}(f) \subset [-\frac{T}{2}, \frac{T}{2}]$ . Consider the function

$$F_p(\xi) := \sum_{k=-\infty}^{\infty} \mathcal{F}(f)(\xi + Tk),$$

which is periodic of period  $T$ . Show that, as a periodic function, the Fourier series of  $F_p$  is

$$\sum_{n=-\infty}^{\infty} \frac{1}{T} f\left(\frac{n}{T}\right) e^{-2\pi i \frac{n}{T} \xi}.$$

7. Given two periodic discrete signals,  $f = \{f(n)\}_{n=0}^{N-1}$  and  $h = \{h(n)\}_{n=0}^{N-1}$ , of period  $N$ , the circular convolution is defined as

$$f \circledast h = \sum_{p=0}^{N-1} f(p)h(n-p) \quad n \in \mathbb{Z}.$$

Prove that  $f \circledast h = h \circledast f$ .

8. Denote by  $\widehat{f}(k)$  de DFT of a discrete signal of size  $N$  ( $N$  even). Define  $\widetilde{f}(\frac{N}{2}) = \widehat{f}(\frac{3N}{2}) = \widehat{f}(\frac{N}{2})$  and

$$\widetilde{f}(k) = \begin{cases} 2\widehat{f}(k) & \text{if } 0 \leq k < N/2 \\ 0 & \text{if } N/2 < k < 3N/2 \\ 2\widehat{f}(k-N) & \text{if } 3N/2 < k < 2N \end{cases}$$

Prove that the discrete signal  $\widehat{f}$  of size  $2N$  satisfies  $\widetilde{f}(2n) = f(n)$ .

9. Show that the bidimensional discrete exponentials

$$e_{k,l}(n, m) := e^{\frac{2\pi i k n}{N}} e^{\frac{2\pi i \ell m}{N}}, \quad 0 \leq k, \ell < N,$$

satisfy

$$L_g e_{k,l}(n, m) = e_{k,l}(n, m) \sum_{p=0}^{N-1} \sum_{q=0}^{N-1} g(p, q) e_{k,l}(-p, -q)$$

where  $L_g f(n, m) = f \circledast g(n, m)$ , for  $g$  and  $f$   $N$ -periodic bidimensional discrete signals.