

ORTHONORMAL BASES FOR SIGNAL AND IMAGE PROCESSING.

1. Given $f : [0, 1] \rightarrow \mathbb{R}$ with $f \in L^2([0, 1])$, extend f to \mathbb{R} to obtain a function \tilde{f} odd with respect to the origin, even with respect to 1 and -1 and 4-periodic. By writing the Fourier series of \tilde{f} in $[-2, 2]$ in terms of sines and cosines show that the cosine coefficients are zero as well as the even sine coefficients. Prove that

$$\left\{ \sqrt{2} \sin\left(\frac{2k+1}{2}\pi x\right) : k = 0, 1, 2, \dots \right\}$$

is an orthonormal basis of $L^2([0, 1])$. This is called the **sine-IV** basis for $L^2([0, 1])$.

2. Show that for a function $f \in L^2(\mathbb{R}) \cap C^2(\mathbb{R})$, the coefficients of f in the block cosine-I basis given by

$$\left\{ \chi_{[n, n+1)}(x) : n \in \mathbb{Z} \right\} \cup \left\{ \chi_{[n, n+1)}(x) \sqrt{2} \cos \pi k(x - n) : n \in \mathbb{Z}, k = 1, 2, \dots \right\}$$

decay, for n fixed, at a rate proportional at least to $1/k^2$.

3. Given $\varepsilon > 0$, choose ψ an even, C^∞ function defined on \mathbb{R} , supported on $[-\varepsilon, \varepsilon]$ such that $\int_{-\varepsilon}^{\varepsilon} \psi(x) dx = \pi/2$. Let $\theta(x) = \int_{-\infty}^x \psi(y) dy$. Show that $\theta(x) + \theta(-x) = \pi/2$. Define $s_\varepsilon(x) = \sin \theta(x)$. Show that $[s_\varepsilon(x)]^2 + [s_\varepsilon(-x)]^2 = 1$.

4. With the same notation as in the previous exercise, let $c_\varepsilon(x) = \cos(\theta(x))$. Let $I = [\alpha, \beta] \subset \mathbb{R}$, $\varepsilon, \varepsilon' > 0$, such that $\alpha + \varepsilon < \beta - \varepsilon'$. The function

$$b_I(x) = s_\varepsilon(x - \alpha) c_{\varepsilon'}(x - \beta)$$

is called a **bell** function associated with the interval $I = [\alpha, \beta]$.

a) Sketch the graph of the bell function b_I .

b) Show that on $[\alpha - \varepsilon, \alpha + \varepsilon]$

- i) $b_I(x) = s_\varepsilon(x - \alpha)$.
- ii) $b_I(2\alpha - x) = s_\varepsilon(\alpha - x) = c_\varepsilon(x - \alpha)$.
- iii) $b_I^2(x) + b_I^2(2\alpha - x) = 1$.

5. Show that the collection of N vectors

$$\mu_k \frac{1}{\sqrt{N}} \left(\sin \frac{k\pi}{N} \left(n + \frac{1}{2} \right) \right)_{n=-N}^{N-1}, \quad k = 1, 2, \dots, N,$$

each one of size $2N$, where $\mu_k = 1$ if $k = 1, 2, \dots, N - 1$ and $\mu_N = 1/\sqrt{2}$, is an orthonormal system.

6. Show that the N vectors given by

$$\mu_k \sqrt{\frac{2}{N-1}} \left(\lambda_n \cos\left[\frac{\pi}{N-1} k n\right] \right)_{n=0}^{N-1}, \quad k = 0, 1, 2, \dots, N-1,$$

each one of size N , where $\lambda_0 = 1/\sqrt{2}$, $\lambda_{N-1} = 1/\sqrt{2}$ and $\lambda_n = 1$ if $n = 1, 2, \dots, N-2$, and $\mu_0 = \mu_{N-1} = 1/\sqrt{2}$, and $\mu_k = 1$ if $k = 1, 2, \dots, N-2$, is an orthonormal basis of the space of signals of size N . This basis corresponds to the one obtained by extending $f = (f(n))_{n=0}^{N-1}$ evenly with respect to $n = 0$.

7. (2 points) This exercise shows how to calculate DCT-I with an induction relation that involves DCT-IV.

a) Regroup the terms $f(n)$ and $f(N-1-n)$, $0 \leq n \leq \frac{N}{2} - 1$, $N = 2^q$, in the DCT-I, to write $\widehat{f}_I(2k)$ as the DCT-I of the signal

$$s(n) = \frac{1}{\sqrt{2}} [f(n) + f(N-1-n)], \quad 0 \leq n \leq \frac{N}{2} - 1.$$

b) With the same technique as in part a), write $\widehat{f}_I(2k+1)$ as the DCT-IV of the signal

$$r(n) = \frac{1}{\sqrt{2}} [f(n) - f(N-1-n)], \quad 0 \leq n \leq \frac{N}{2} - 1.$$

c) Using that, with a fast algorithm, the number of operations to calculate DCT-IV of size N is $O(N \log_2 N)$ and parts a) and b), show that with the above algorithm, the number of operations needed to calculate DCT-I of size N is also $O(N \log_2 N)$.

8. Show that the number $B_j^{(2)}$ of orthogonal bases of the space of discrete images of size N^2 ($N = 2^L$) in a bi-dyadic tree of depth j , $1 \leq j \leq L$, satisfies

$$2^{4^{j-1}} \leq B_j^{(2)} \leq 2^{\frac{4}{3} 4^{j-1}}.$$

9. Consider the signal f of size $N = 8$ given by

$$f = (8, 16, 24, 32, 40, 48, 56, 64).$$

a) Compute the DCT-I of f , rounding the result to the nearest integer. Compress the signal 50% by setting to zero the DCT-I coefficients in positions 4, 5, 6, and 7. Find now the inverse DCT-I of this compressed signal, and, after rounding, observe that is similar to the original one.

b) Take now the orthonormal basis of \mathbb{C}^8 given by

$$\left\{ \lambda_k \frac{1}{2} \left(\cos \frac{\pi k n}{4} \right)_{n=0}^7 \right\}_{k=0}^4 \cup \left\{ \frac{1}{2} \left(\sin \frac{\pi k n}{4} \right)_{n=0}^7 \right\}_{k=1}^3.$$

where $\lambda_0 = \lambda_4 = \frac{1}{\sqrt{2}}$ and $\lambda_1 = \lambda_2 = \lambda_3 = 1$. Repeat the process in a), setting now to zero the frequencies $k = 3$ and $k = 4$ of cosines, and the frequencies $k = 2$ and $k = 3$ of sines. Observe that the final result is somehow different than the original signal.